CSE2021 Computer Organization **CSE2021** Computer Organization Instructor: Gulzar Khuwaja, PhD Email: khuwaja@cse.yorku.ca Tel: (416) 736-2100 x 77874 Instructor: Gulzar Khuwaja, PhD Course Website: Department of Electrical Engineering https://wiki.eecs.yorku.ca/course_archive/2014-15/S/2021/ & Computer Science Schedule: Lassonde School of Engineering Lectures: R 7:00 - 10:00 pm Room CLH M (206) York University Labs: M 7:00 - 10:00 pm Room LAS 1006 Office Hrs: R 5:00 - 06:30 pm Room LAS 2018 M< M< Chapter 1 — Computer Abstractions and Technology — 2









	Moore's Law				
	Year 4004 8008 8080 8086 286 386™ 486™ DX Pentium® Pentium II Pentium II Pentium II Pentium 4	r of introduction 1971 1972 1974 1978 1982 1985 1989 1993 1997 1999 2000	Transistors 2,250 2,500 5,000 29,000 120,000 275,000 1,180,000 3,100,000 7,500,000 24,000,000 42,000,000		
≤<	Chapter 1 — Computer Abstractions and Technology —				



























	Example						
 Alternative <u>compiled</u> code sequences using instructions in classes A, B, C 							
Cla	ISS	А	В	С			
CP	I for class	1	2	3			
IC	in sequence 1	2	1	2			
IC	in sequence 2	4	1	1			
 Sequel Clock = 2x' = 10 	 Sequence 2: IC = 6 Clock Cycles = 4x1 + 1x2 + 1x3 = 9 			i			
Avg. CPI = 10/5 = 2.0 Avg. CPI = 9/6 = 1.5							
Chapter 1 – Computer Abstractions and Technology – 5							

